

AutoFuel Computer (AFC)				AFC		
Pin	Disc. FROM	Color	TO	Pin	AWG	Length (IN)
1	AutoFuel Computer - GND	BLK	GND BUS		20	
				GND	16	
2	AutoFuel Computer - GND	BLK	GND BUS		20	
3						
4	HI Sensor GND	BLK	LFPT #2	f	24	
5	HI Sensor PWR	WHT	LFPT #2	g	24	
6	HI Sensor SIGNAL	WHT	LFPT #2	h	24	
7	LO Sensor GND	BLK	LFPT #2	v	24	
8	LO Sensor PWR	WHT	LFPT #2	w	24	
9	LO Sensor SIGNAL	WHT	LFPT #2	x	24	
10						
11						
12	Left TipTxfr (Sensor AFC to WP #1)	WHT	PIPR	ii	20	
13						
14						
15						
16	Right Tip Txfr (Sensor AFC to WP # 1)	WHT	PIPR	j	20	
17						
18						
19	Left SW (Auto)	WHT	PIPL	J	16	
20	Left SW (HI Press Control)	WHT	PIPL	P	16	
21						
22	Right SW Hi Press Control	WHT	PIPL		16	
23	Right SW (Auto)	WHT	PIPL	K	16	
24	Left Tip Sensor GND	ORG	FWL	L	20	
25	Left Tip Sensor PWR	WHT	FWL	M	20	
26	Left Tip Sensor SIG	BLU	FWL	N	20	
27						
28						
29						
30						
31	Left Main Txfr Valve (Sw to AFC)	WHT	PIPR	S	20	
32						
33						
34	Right Tip Sensor GND	WHT	FWR	L	20	
35	Right Tip Sensor PWR	WHT	FWR	M	20	
36	Right Tip Sensor SIG	WHT	FWR	N	20	
37						
38						
39						
40						
41	Right Main Txfr Valve (Sw to AFC)	WHT	PIPR	T	20	
42						
43						
44	Warning Panel Left TXFR	WHT	WP #1	J2-24	24	
45	Warning Panel Right TXFR	WHT	WP #1	J2-22	24	
46	Warning Panel BINGO	WHT	WP #1	J1-15	24	
47						
48						
49	AutoFuel Computer - PWR	RED	RPP #3		20	
				p	16	
50	AutoFuel Computer - PWR	RED	RPP #3		20	

AMP 205211-1 Receptical

50 Pins

Total:



Wire Size

Length (FT)

24 AWG =

20 AWG =

16 AWG =

20C3 =